

MIXER POWER AMPLIFIER

(1) 기 능

본 기기는 6 개의 마이크 입력과 5 개의 보조 입력이 특징이며, 외부 시그널 프로세서접속이 가능한 단자를 가지고 있어야 한다. 정격출력은 240W 로서 두 개의 스피커 셀렉터와 녹음, 라인출력 그리고 하이 와 로우 임피던스 출력단자를 제공해야 한다.

(2) 성 능

- 사용전원 : 220 – 230V AC, 50/60 Hz
- 정격출력 : 240W
- 소비전력 : 532W (rated output), 220W (EN60065)
- 주파수 응답 : 50-20,000Hz (± 3 dB)
- 왜곡 : 2% or less at 1khz, rated power
- 입력 : MIC 1 – 6: – 60dB, 600 Ω , electronically-balanced, combined type of XLR-3-31equivalent and phone jack
AUX 1 – 2: – 20dB, 600 Ω , electronically-balanced, combined type of XLR-3-31 equivalent and phone jack
AUX 3 – 4: – 20dB*, 10k Ω , unbalanced, RCA pin jack
AUX 5: – 20dB*, 10k Ω , unbalanced, combined type of XLR-3-31 equivalent and phone jack
PWR AMP IN: 0dB*, 600 Ω , unbalanced, RCA pin jack
- 출력 : REC: 0dB, 600 Ω , unbalanced, RCA pin jack

LINE: 0dB, 600Ω , unbalanced, RCA pin jack

SPEAKER SELECTOR: 2 zone, high impedance(100V line/ 42Ω), individual selector key, M4 screw terminal

Direct speaker out: High impedance(100V line/ 42Ω), M4 screw terminal Low impedance(4-16Ω), M4 screw terminal

- 팬텀전원 : ON or OFF for each MIC 1-6 with switch setting (+17V DC)

- S/N 비(Band Pass:20-20,000Hz) : Over 100dB (Master volume: min), Over

76dB (Master volume: max), Over 60dB (MIC 1 – MIC 4), Over 53dB (MIC 5, 6), Over

76dB (AUX 1 – AUX 5)

- 톤 컨트롤 : Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz

- 컨트롤 입력 : REMOTE VOLUME: M3 screw terminal

POWER REMOTE: No-voltage make contact input, open voltage: 24V DC

(when the unit's power is OFF), short-circuit: under 10mA, M3 screw

terminal

- 인디케이터 : 5 point LED output level meter, Power indicator LED,

Zone indicator LED

- 동작 온도 : -10°C to +40°C

- 크기 (W x H x D) : 420 x 107.7 x 367 mm

- 무게 : 13.5kg

위 사양 및 동등 이상품이어야 한다.