

# FIREMAN'S MICROPHONE

## (1) 기 능

본 소방관용 마이크로폰은 1 개의 비상키, 3 개의 기능키, 1 개의 토크키 그리고 이와 연관된 표시 램프를 제공해야 한다. 모든 기능은 설정 소프트웨어를 이용하여 기능키에 할당 되어야 한다. 리모트 마이크로폰 확장기를 연결하면 10 개의 기능키와 인디케이터 수를 확장할 수 있어야 한다.

## (2) 성 능

- 사용전원 : 24 V DC
- 전류소비 : 120 mA, 660 mA (with 3 Extension connected)
- 왜곡 : 1% or less
- 주파수 응답 : 200 - 15,000 Hz
- S/N 비 : 55 dB or more
- 마이크로폰 : Unidirectional dynamic microphone with talk key, compressor  
(on/off switchable)
- 볼륨 컨트롤 : Microphone volume control, Buzzer volume control
- 커넥션 케이블 : Shielded CPEV cable or Category 5 Shielded twisted pair straight cable  
for LAN(CAT5-STP), M3 screw terminal
- 최대케이블길이 : 800 m

- 확장 연결 수 : max. 3 unit
  
- 오퍼레이션 : Emergency key, Evacuate key, Emergency reset key, CPU  
switch, Reset switch
  
- 인디케이터 : Power indicator, Emergency indicator, Communication failure indicator,  
CPU OFF indicator, Evacuation announcement indicator, Alert  
announcement indicator, Emergency reset indicator, Microphone in-use  
indicator, Emergency broadcast equipment in-use indicator
  
- 동작온도 : 5°C to +45°C
  
- 동작습도 : 5% to 95% RH (no condensation)
  
- 마감 : ABS resin, blueish gray
  
- 치수 : 200(W) × 215(H) × 82.5(D) mm
  
- 중량 : 1.1kg

위 사양 및 동등 이상품 이어야 한다.